

1		2		3		4																																												
电机参数							接线图 (CW)																																											
机种名	步进角	电阻	电感	电流	保持力矩	机身高L																																												
60HK88	1.8°	0.55 Ω	1.6mH	5.0A	3000mN.m	87mm																																												
60HK100	1.8°	0.65 Ω	1.7mH	5.5A	3200mN.m	99.5mm																																												
单位: mm																																																		
<table><tr><td colspan="6">励磁顺序 (2相励磁)</td></tr><tr><td rowspan="6">CW ↓</td><td>Step</td><td>A</td><td>B</td><td>C</td><td>D</td><td rowspan="6">CCW ↑</td></tr><tr><td>1</td><td>+</td><td>+</td><td>-</td><td>-</td></tr><tr><td>2</td><td>-</td><td>+</td><td>+</td><td>-</td></tr><tr><td>3</td><td>-</td><td>-</td><td>+</td><td>+</td></tr><tr><td>4</td><td>+</td><td>-</td><td>-</td><td>+</td></tr><tr><td>5</td><td>+</td><td>+</td><td>-</td><td>-</td></tr><tr><td>6</td><td>-</td><td>+</td><td>+</td><td>-</td></tr></table> <p>从安装面看转向 (CW/CCW)</p>								励磁顺序 (2相励磁)						CW ↓	Step	A	B	C	D	CCW ↑	1	+	+	-	-	2	-	+	+	-	3	-	-	+	+	4	+	-	-	+	5	+	+	-	-	6	-	+	+	-
励磁顺序 (2相励磁)																																																		
CW ↓	Step	A	B	C	D	CCW ↑																																												
	1	+	+	-	-																																													
	2	-	+	+	-																																													
	3	-	-	+	+																																													
	4	+	-	-	+																																													
	5	+	+	-	-																																													
6	-	+	+	-																																														
				一般公差	±0.3/1°	名称	电机规格书 (60HK)																																											
				材质	-----	版 本	00																																											
				表面处理	-----	设 计	simon23.05.20																																											
				视图		比例	审 核	周绍兵23.05.20																																										
00	00初版		周绍兵23.05.20				批 准	周绍兵23.05.20																																										
版本	变更内容		担当者	STEP MOTOR				页数	1/1																																									